



## SCR-LNB

SCR-LNB with 2 legacy outputs

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588178861	beige	0017/8886	344 g	292 g	14.50 x 6.00 x 11.50 cm	12.30 x 6.50 x 15.00 cm

### TOP FEATURES

4 Receiver mit SCR-Unterstützung anschließbar

2 Receiver über Legacy-Ausgang anschließbar

SCR-Protokoll gemäß EN 50494

Wetterschutzgehäuse

Feed-ø 40 mm

#### LOCAL OSCILLATOR

Low band : 9.75 GHz

High band : 10.6 GHz

Accuracy : ± 1 MHz

Temperature drift : ± 3 MHz

Phase noise : -80 dBc/Hz @10kHz

#### LNB CONTROL

Vertical : 11,5 ... 14 V

Horizontal : 16 ... 19 V

Band switch : 22 kHz

DiSEqC : 1.0

#### AMBIENT OPERATING CONDITIONS

Ambient temperature : -30 ... 60 °C

#### INPUT FREQUENCY RANGE

Low band : 10.7 ... 11.7 GHz

High band : 11.7 ... 12.75 GHz

#### NOISE FACTOR

Noise figure : 1 dB

#### OUTPUT FREQUENCY RANGE

Low band : 950 ... 1950 MHz

High band : 1100 ... 2150 MHz

#### POWER SUPPLY

Power consumption : max. 280 mA @13,5 V

#### PREPARED FOR

Number of clients : 6

Number of orbit positions : 1

#### SINGLE-CABLE OUTPUT

Output frequency : 950 ... 2150 MHz

Number of output channels : 4

Frequency of the output channels : 1210, 1420, 1680, 2040 MHz

#### TECHNICAL DATA

Outputs : 3 ; 1x SCR (gilded), 2x Legacy

Impedance : 75 Ω

Feed reception : ø 40 mm

Amplification : 57 dB

Connector type : F-Buchse

#### SCOPE OF DELIVERY

TechniSat SCR-LNB