



F plug Self-Install™ 3.9 set

3.9 Professional Installation kit for home

EAN	Item no.	Colour	Weight (Box)	Weight	Box
4019588633711	0006/3371	silver	6 g	6 g	12,2 x 18,7 x 2,5 cm

TOP FEATURES

Easy and safe installation in seconds
with 6 Self-Install™ F-connectors 3.9

including stripping tool
suitable for 100 dB Mini-CoaxSat 2150,
double mini-coax cable and Multymedia
cable 4 from TechniSat

suitable for all coaxial cables 0.8/3.6
suitable for all coaxial cables with approx.
3.5 mm dielectric and 5.7 - 6.2 mm outer
diameter

ATTENUATION

10 MHz : 0,03

100 MHz : 0,03

450 MHz : 0,03

800 MHz : 0,05

862 MHz : 0,06

1000 MHz : 0,06

2250 MHz : 0,06

RETURN LOSS

30 - 65 MHz : ≥ 38 dB

65 - 470 MHz : ≥ 38 dB

470 - 1800 MHz : ≥ 38 dB

1800 - 2450MHz : ≥ 36 dB

TECHNICAL DATA

Impedance : 75 Ω

TRANSFER IMPEDANCE

5MHz : $\leq 0,2$

30 MHz : $\leq 0,2$

SCOPE OF DELIVERY

6 x F-connectors Self-Install™ 3.9
1 x stripping tool