



DIGITRADIO 51

DAB+/FM clock radio with two independent easy set alarms

EAN	Item no.	Colour	Weight (Box)	Weight	Device (W x H x D)	Box
4019588100084	0000/4981	anthracite	650 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm
4019588800014	0001/4981	white	648 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm

TOP FEATURES

DAB+ digital radio

RDS-PLL VHF radio

Station memory (2 DAB+/2 VHF)

Date and time display

Two wake-up times adjustable

Alarm via acoustic signal or radio station

Adjustable alarm frequency

Snooze and sleep timer functions

Large LCD display with illumination and separate time display

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative air humidity (non-condensing)

Ambient temperature : 5 - 35 °C

CONNECTIONS

Headphone connection jack (3,5mm) : 1

DISPLAY

Size : 4,5 in

Dimmable : Yes

Type : LCD

HANDLING/COMFORT

Clock : Yes

Automatic time reset following a power cut : Yes

Alarm : Yes

Sleep timer : Yes

Snooze : Yes

Favourites programme manager FM : 2

Favourites programme manager DAB+ : 2

LOUDSPEAKERS

Mono speakers : Yes

Output performance : 1,5 W (RMS)

OTHER FEATURES

OSD languages : English, German, French, Italian, Danish, Spanish

POWER CONSUMPTION

In operation : 3 W

Standby : 0,44 W

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Mains adapter : DC 6 V / 500 mA

Type of power supply : external

RADIO / RECEPTION

DAB+ : 174 - 240 MHz

FM/RDS : 87,5 - 108 MHz

Aerial : DAB/FM aerial

RADIO TYPE

stationary radio : Yes

SCOPE OF DELIVERY

DigitRadio 51, Power Supply, Instruction Manual