



Scene switch 1

4 buttons remote control

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588502093	white	0000/9521	60 g	26 g	5.00 x 5.00 x 1.50 cm	8.00 x 8.00 x 3.00 cm

TOP FEATURES

TechniSat smart home component

Integration via TechniSat CONNECT-App

Remote control with 4 buttons

Control 8 different scenes - Press and hold for each button

Installation on the wall or use as portable remote control

Power supply: rechargeable batterie or USB micro 5V

Z-Wave™ wireless sensor (868.42 MHz)

AMBIENT OPERATING CONDITIONS

IP class : 20

Ambient temperature : 0 ... 40 °C

Humidity : 10 - 75 %

CONNECTIONS

USB charging : Yes

FUNK COMMUNICATION

Telecommunication : Z-Wave Plus

Range inside : max. 40 m

Range outside : max. 100 m

operating frequency : 868.42 MHz

POWER SUPPLY

Nominal voltage : 3.6 V

Battery charge via USB : Yes

Battery life : bis zu 6 Monate

Rechargeable battery : Li-Ion LIR2450

Non rechargeable battery : 1.5 V AAA alkaline, class III

SCOPE OF DELIVERY

Szenenschalter 1, batterie LIR2450,USB charging cable, double-sided mounting tape, manual