



DIGITRADIO 307

DAB+/FM designer radio

| EAN | Colour | Item no. | Weight (Box) | Weight | Device (W x H x D) | Box |
|---------------|---------|-----------|--------------|---------|---------------------|-----------------------|
| 4019588039476 | schwarz | 0000/3947 | 1,9 kg | 1,35 kg | 22 x 13,9 x 16,5 cm | 30,5 x 17,5 x 19,7 cm |
| 4019588139473 | weiß | 0001/3947 | 1,9 kg | 1,35 kg | 22 x 13,9 x 16,5 cm | 30,5 x 17,5 x 19,7 cm |

TOP FEATURES

DAB+ digital radio

FM radio (with RDS and PLL)

Favourites memory slots (DAB+/ FM)

TFT colour display (2.4")

Date and time display

Two radio alarms available

Sleep timer

excellent tone

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative air humidity (non-condensing)

Ambient temperature : 5 - 35 °C

CONNECTIONS

Audio in/AUX in : Yes

Headphone connection jack (3,5mm) : 1

DIMENSIONS / WEIGHT

Stationary : Yes

DISPLAY

Size : 2,4 in

Slide show/catSLS : Yes

Dimmable : Yes

Type : TFT colour display (2.4")

HANDLING/COMFORT

Clock : Yes

Alarm : Yes

Sleep timer : Yes

Snooze : Yes

Manual control elements : Yes

Favourites programme manager FM : 20

Favourites programme manager DAB+ : 20

LOUDSPEAKERS

Mono speakers : Yes

Output performance : 5 W (RMS)

OTHER FEATURES

OSD languages : English, German, French, Polish, Italian, Dutch, Norwegian, Danish

POWER CONSUMPTION

In operation : 14,5 W

Standby : <1 W

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Mains adapter : DC 9V / 1.600mA

Type of power supply : External

RADIO / RECEPTION

DAB+ : 174 - 240 MHz

FM/RDS : 87,5 - 108 MHz

Aerial : DAB/FM-telescopic antenna

RADIO TYPE

stationary radio : Yes

SCOPE OF DELIVERY

DIGITRADIO 307, power supply, user manual