



## DigiPal 2TX e

Digital DVB-T receiver for the reception of Free-to-Air television programmes

EAN	Item no.	Colour
4019588134928	0013/4920	silver

<b>TECHNISAT ADDED VALUE SERVICES</b>	Total programme memory: 4000	Reception range 1: 174 ... 230 MHz
AUTOINSTALL: Yes	OSD languages: Danish, English, Swedish, Dutch, French, Greek, Italian, Spanish, Finnish, Czech	Reception range 2: 470 ... 862 MHz
<b>CONNECTIONS</b>	<b>POWER CONSUMPTION</b>	<b>SCOPE OF DELIVERY</b>
Digital electric audio output: Yes	Standby LED: < 0,2 W	DigiPal 2 TX e, remote control with batteries, power cable, scart cable, instruction manual
Audio out analogue: Yes	In operation: 4 W	
RS-232: 1	<b>POWER SUPPLY</b>	
<b>DISPLAY</b>	Mains adapter: internal	
576i: Yes	Frequency: 47 ... 63 Hz	
SD: Yes	Nominal voltage: 180 ... 250 V	
<b>HANDLING/COMFORT</b>	<b>TUNER</b>	
Sleep timer: Yes	Tuner type: DVB-T	
Clock: Yes	Reception on: SD (MPEG-2)	
<b>OTHER FEATURES</b>	<b>TUNER - TERRESTRIAL</b>	

KEYFEATURES	
AutoInstall	EPG