




TECHNILAN 4/4 Active

Coax home network combiner for 4 subscribers

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588036376	blue/yellow	0000/3637	700 g	200 g	14 x 3,3 x 12 cm	23 x 6 x 15,2 cm

TOP FEATURES

Home network via coaxial cable

Can be used with any TechniSat multi-switch

Can be used with Quattro-Switch-LNB

4 Subscribers

Integrated network modem

Peer-to-peer network for Ethernet, 2 x LAN connection

AMBIENT OPERATING CONDITIONS

Ambient temperature : 0 ... 35 °C

Humidity : 10 ... 75 %

GENERAL CHARACTERISTICS

Top features : Home network via coaxial cable

Top features : Can be used with any TechniSat multi-switch

Top features : Can be used with Quattro-Switch-LNB

Top features : 4 Subscribers

Top features : Integrated network modem

Top features : Peer-to-peer network for Ethernet, 2 x LAN connection

POWER CONSUMPTION

In operation : 3,25 W typisch

POWER SUPPLY

Nominal voltage : 100 ... 240 V

Frequency : 50 ... 60 Hz

Mains adapter : external 13 V DC / 3 A

Power consumption : typ. 250 mA

SCOPE OF DELIVERY

TechniLAN 4/4 Active, Plug-in power supply unit, 4 x F-Quick connector