



## F plug Self-Install™ 4.9 set

4.9 Professional Installation kit for home

EAN	Item no.	Colour	Weight (Box)	Weight	Box
4019588633704	0006/3370	silver	100 g	100 g	12.20 x 18.70 x 2.50 cm

### TOP FEATURES

Easy and safe installation in seconds  
with 6 Self-Install™ F-connectors 4.9

including stripping tool

Suitable for 115dB and 120dB cables from TechniSat

Suitable for all RG6 coaxial cables 1.0/4.6

Suitable for all coaxial cables with approx. 4.5 mm dielectric and 6.6 - 7.0 mm outer diameter

### ATTENUATION

10 MHz : 0.03

100 MHz : 0.03

450 MHz : 0.03

800 MHz : 0.05

862 MHz : 0.06

1000 MHz : 0.06

2250 MHz : 0.06

### RETURN LOSS

30 - 65 MHz :  $\geq 38$  dB

65 - 470 MHz :  $\geq 38$  dB

470 - 1800 MHz :  $\geq 26$  dB

1800 - 2450MHz :  $\geq 26$  dB

### TECHNICAL DATA

Impedance : 75  $\Omega$

### TRANSFER IMPEDANCE

5MHz :  $\leq 0.2$

30 MHz :  $\leq 0.2$

### SCOPE OF DELIVERY

6 x F-connectors Self-Install™  
4.9<br>1 x stripping  
tool