



Premium account required. You can find all information about Spotify Premium at www.spotify.com/premium.

DIGITRADIO 510

Stereo digital radio for the reception of DAB+, FM and internet radio with multiroom streaming and Spotify Connect

EAN	VPE Karton	Colour	VPE Palette	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588049 697	4	black	32	0000/4969	3,1 kg	2,09 kg	35 x 12,53 x 13,11 cm	39,8 x 21,3 x 18,8 cm
4019588149 694	4	white	32	0001/4969	3,1 kg	2,09 kg	35 x 12,53 x 13,11 cm	39,8 x 21,3 x 18,8 cm

TOP FEATURES

DAB+ Digital radio

RDS-PLL VHF radio

Internet radio via WiFi

Compatible with Spotify Connect

3,2" TFT color display

Bluetooth audio streaming (reception)

Multiroom streaming

Intuitive operation concept via 2 setting regulators

Remote control via MyDigitRadio app (iOS, Android)

Remote Control

WLAN

WLAN : 802.11 a / b / g / n (2.4 GHz and 5 GHz band supported)

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend)

Ambient temperature : 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version : 2.1 + EDR

AVRCP (Audio Video Remote Control Profile) : ja

A2DP (Advanced Audio Distribution Profile) : ja

CONNECTIONS

Audio in/AUX in : Yes

Headphone connection jack (3,5mm) : 1

DISPLAY

Size : 3,2 in

Resolution (vertical and horizontal) : 240 x 320

RadioVIS : Yes

Type : TFT color display

Slide show/catSLS : Yes

Dimmable : Yes

HANDLING/COMFORT

Alarm : Yes

Sleep timer : Yes

Snooze : Yes

Favourites programme manager DAB+ : 10

Favourites programme manager FM : 10

LOUDSPEAKERS

Stereo speakers : Yes

Output performance : 20 W (RMS)

Stereo : 2 x 10 W

NETWORK & COMMUNICATION

Bluetooth : Yes

NFC : Yes

OTHER FEATURES

OSD languages : English, German, French, Polish, Italian, Dutch, Norwegian, Danish, Swedish, Finnish, Spanish, Portuguese, Turkish

POWER CONSUMPTION

Power consumption in standby mode with active network connection : 5,16 W

In operation : 36 W

Standby : 0,89 W

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Mains adapter : DC 18 V / 2000 mA

Type of power supply : external

RADIO / RECEPTION	RADIO TYPE	STREAMING
DAB+ : 174 - 240 MHz	stationary radio : Yes	Spotify : Yes
FM/RDS : 87,5 - 108 MHz		Bluetooth audio streaming : Yes
Internet radio : Yes		Audio streaming : Yes
Aerial : DAB / UHF telescopic aerial		SCOPE OF DELIVERY
		DigitRadio 510, power supply, remote control, user manual