



DIGITRADIO 51

DAB+/FM clock radio with two independent easy set alarms

EAN	Item no.	Colour	Weight (Box)	Weight	Device (W x H x D)	Box
4019588100084	0000/4981	anthracite	650 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm
4019588800014	0001/4981	white	648 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm

TOP FEATURES		
DAB+ digital radio	Date and time display	Adjustable alarm frequency
RDS-PLL VHF radio	Two wake-up times adjustable	Snooze and sleep timer functions
Station memory (2 DAB+/2 VHF)	Alarm via acoustic signal or radio station	Large LCD display with illumination and separate time display
AMBIENT OPERATING CONDITIONS	LOUDSPEAKERS	stationary radio : Yes
Humidity : 5 - 90 % relative air humidity (non-condensing)	Mono speakers : Yes	SCOPE OF DELIVERY
Ambient temperature : 5 - 35 °C	Output performance : 1,5 W (RMS)	DigitRadio 51, Power Supply, Instruction Manual
CONNECTIONS	OTHER FEATURES	
Headphone connection jack (3,5mm) : 1	OSD languages : English, German, French, Italian, Danish, Spanish	
DISPLAY	POWER CONSUMPTION	
Size : 4,5 in	In operation : 3 W	
Dimmable : Yes	Standby : 0,44 W	
Type : LCD	POWER SUPPLY	
HANDLING/COMFORT	Nominal voltage : 230 V	
Clock : Yes	Frequency : 50 Hz	
Automatic time reset following a power cut : Yes	Mains adapter : DC 6 V / 500 mA	
Alarm : Yes	Type of power supply : external	
Sleep timer : Yes	RADIO / RECEPTION	
Snooze : Yes	DAB+ : 174 - 240 MHz	
Favourites programme manager FM : 2	FM/RDS : 87,5 - 108 MHz	
Favourites programme manager DAB+ : 2	Aerial : DAB/FM aerial	
	RADIO TYPE	