



DIGITRADIO 52

DAB+/FM clock radio with wireless charging function

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588039148	anthracite	0000/3914	920 g	608 g	16 x 7 x 13 cm	23 x 8,2 x 14,5 cm
4019588139145	white	0001/3914	920 g	608 g	16 x 7 x 13 cm	23 x 8,2 x 14,5 cm

TOP FEATURES

DAB+ digital radio

Wireless charging for charging smartphones

Favourites memory slots (20 for DAB+ and 20 for FM)

Date and time display

Two wake-up times adjustable

Alarm via acoustic signal or radio station

Adjustable alarm frequency

Snooze and sleep timer functions

Large LCD display with backlight

RDS-PLL VHF radio

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative air humidity (non-condensing)

Ambient temperature : 5 - 35 °C

CONNECTIONS

USB : 1

Headphone connection jack (3,5mm) : 1

DISPLAY

Size : 4,7 in

Dimmable : Yes (automatisch mit Lichtsensor)

Type : LCD

FUNCTIONS

USB charging function : Yes

Wireless charging : Yes (compatible with the Qi charging standard)

HANDLING/COMFORT

Clock : Yes

Automatic time reset following a power cut : Yes

Alarm : Yes

Sleep timer : Yes

Snooze : Yes

Favourites programme manager DAB+ : 20

Favourites programme manager FM : 20

LOUDSPEAKERS

Stereo speakers : Yes

Output performance : 2 W (RMS)

Stereo : 2 x 1 W

OTHER FEATURES

OSD languages : English, German, French, Italian

POWER CONSUMPTION

In operation : 12 W

Standby : 0,75 W

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Mains adapter : DC 5.5 V / 2000 mA

Type of power supply : external

RADIO / RECEPTION

DAB+ : 174 - 240 MHz

FM/RDS : 87,5 - 108 MHz

Aerial : DAB/FM aerial

RADIO TYPE

stationary radio : Yes

SCOPE OF DELIVERY

DIGITRADIO 52, power supply unit, instruction manual