



TECHNISTAR S6 Int. Edt.

HDTV digital satellite receiver with USB-PVR function

EAN	Item no.
4019588647176	0006/4717

TOP FEATURES

HDTV tuner (DVB-S/S2)

DVRready: Digital video recorder function for recording to USB hard drive

Timeshift in connection with USB hard drive

Operation on 12V

Multimedia streaming on home network (via UPnP, server)

Electronic program guide (EPG)

MULTIMEDIA

DVR function : Ja

DVR storage medium : via USB

Timeshift : Yes

Recordings edition function : Yes

Recordings folder management : Yes

AMBIENT OPERATING CONDITIONS

Ambient temperature : 5 ... 35 °C

Humidity : 10 ... 75 %

LNB CONTROL

Vertical : 14 V

Horizontal : 18 V

Band switch : 22 kHz

Current consumption : 400 mA

DiSEqC : 1.0 / 1.2 / SCR1 / SCR2

TECHNISAT ADDED VALUE SERVICES

AUTOINSTALL : Yes

TECHNIFAMILY : Yes

SFI : Yes

ISIPRO : Yes

INTERNET/NETWORK

Internet speed test : Yes

AUDIO

audio_klare_sprache : Ja über DVB

CONNECTIONS

HDMI™ (out) : 1

USB : 1 (USB 2.0)

Common Interface Plus (CI+) : 1

Smartcard reader : 1

Digital electric audio output (S/PDIF) : 1

audio/video output analog (3.5 mm jack) :
Yes TechniSat specific adapter set necessary (available at 0000/3649)

Ethernet 10/100 (RJ-45) : 1

F socket : 1

DC IN : 1

DECODER

Video decoder : MPEG-2 MP@HL/ML, H.264/MPEG-4 AVC

Audio decoder : MPEG-1 & MPEG-2 Layer I, II, III

DECRYPTION SYSTEM

Conax : Yes

CI+ : Yes (v1.3)

DISPLAY

Freeze frame : Ja

Zoom : Nein

SD : Yes

HD : Yes

1080p : Yes

1080i : Yes

720p : Yes

576p : Yes

576i : Yes

Type : 7 segment, 4 digits, white

HANDLING/COMFORT

Page memory : 1.000

Teletext subtitles : Yes

Media Player : Yes

Channel presets : 9.999

Teletext : Yes

Clock : Yes

Ideal for camping : Yes

Sleep timer : Yes

Alarm : Yes

HOTEL MODE

Protected access to hotel mode : Ja

Customisable start screen : Ja

Lockable volume : Ja

Menu locking : Ja

Control panel lock : Ja

Integrated LED clock : Ja

Selectable start source : Ja

Selectable start channel : Ja

OTHER FEATURES

OSD languages : German, Danish, English, French, Greek, Italian, Dutch, Norwegian, Polish, Portuguese, Russian, Swedish, Spanish, Czech, Turkish, Hungarian

Internet radio : Yes

POWER CONSUMPTION	SUPPORTED FORMATS & CODECS	TUNER
In operation : 4,8 W without LNB	Video-Codecs : MPEG-2, MPEG-4, H.264	Tuner type : Single-Tuner
Standby : < 0,3 W	Video-Formats : M4V, MP4, MKV, MOV, MPG, TS, TS4, Xvid, M2TS, AVI, ASF	DVB-S tuner : 1
POWER SUPPLY	Picture-Formats : BMP, JPEG, GIF, PNG, TIFF	Single Cable Solution (SatCR) : SCR1 = EN50494, SCR2 = EN50607
Nominal voltage : 230 V	Audio-Formats : WAV, MP3, AAC, FLAC, MP2, OGG, DDAC3, AIFF	Satellite radio : Yes
Frequency : 50 Hz	TECHNISAT CONNECT	Internet radio : Yes
Mains adapter : external DC 12V/2A	Control : Yes	Reception on : HD-TV, SD-TV, DVB radio
STREAMING	SFI : Yes	TECHNIROUTER ready : Yes
Cloud store : Ja		TUNER - SAT
DLNA Client : Yes		Reception range : 950 ... 2.150 MHz
		Viterbi rates : 1/2, 2/3, 3/4, 5/6, 7/8
		DVB-S : QPSK
		DVB-S : 2 ... 45
		DVB-S2 : 8PSK - QPSK
		DVB-S2 : 2 ... 45
		FEC : Viterbi and Reed-Solomon
		SCOPE OF DELIVERY
		TECHNISTAR S6, remote control with batteries, external mains adapter, HDMI cable, quick start guide EN/FR/NL/CZ



The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI trade dress and the HDMI Logos are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.